




User Manual

**All-In-One Solar
Courtyard /Street LED Light**





-
- ① The switch
 - ② PIR
 - ③ Light panel
 - ④ Assembling bolt
 - ⑤ Gasket
 - ⑥ Hoop
 - ⑦ Nut
 - ⑧ Solar panel

Main features:

- 1).Elegant Integrated Design , Aluminum alloy case.
- 2).72LEDs super bright , 3000Lumens brightness
- 3).22.7W solar panel and battery can be replaced.
- 4).Night sensor+PIR motion sensor
- 5).120° wide lighting angle.
- 6).Can support 3 nights!
- 7).Easy to install and Auto on/off/PIR.

Electrical Characteristics:

| | |
|---------------------|--|
| Solar panel | 22.7W, 10years span life. |
| Li-ion battery | 3.7V 39000mAh |
| Led | 72 LEDs, 3000Lumens |
| Charging time | 9-10 hours |
| Lighting mode | Auto light at night with PIR motion sensor till dawn |
| Lighting time | More than 3 nights |
| Ray sensor | <10Lux |
| PIR sensor | 5~8m, 120° |
| Waterproof | IP65 |
| Install height | 4~5 m |
| Material | Aluminum alloy+steel glass |
| Size | 1098*227*164mm |
| Working temperature | -25 ℃ to 65℃ |
| Warranty | 2 years |


Application:

Courtyard/Garden/Park/Street/Roadway/Pathway
/Parking lot/private road/Sidewalk/Public square
/Plaza/Campus/Airfield/Farm&Ranch/Perimeter Security
/Wildlife Area/Remote Area/Military Base

Operation Instructions:

1 How to unlock the working system?

The internal battery is locked from factory for safety shipment ,so users have to use supplied key pin to click the “on/off” socket and unlock the battery and lighting system.




If need to lock(turn off) the light , please use the pin to click the on/off socket again.

2.How to install the device?

Please notice to install the light to the place without any shade and better face to sun light directly for better charging.



For street/roadway lighting, we suggest to install 15M distance between each light.



Working process instructions

Use the supplied key pin to click the "on/off" socket to unlock the battery

Please fasten the light to the pole by the bolt




Step1:Light switch off for sun charging in daytime.

①




②

Step2: It will turn on 500lumens dim light at night with PIR function till dawn




Step4:When people leaving 5~8m away, the light will turn on dim light again




Step3: When people come near 5-8m, the light will turn on 3000lumens brightness and delay 30s

③



④

Replace the inside battery work as the picture when the battery span life is in the end.



Special Note:

- 1).Please notice to unlock the battery and working system by supplied Key Pin before install.
- 2).Please give bright sunlight charging over 5 hours before first time use,as the battery is very low from factory.
- 3).If there is no good sunlight in 3 months ,the battery may be out of power so you have to charge it by bright sunlight ,when it's fully charged, please use Supplied Key Pin to unlock the device and lighting system ,otherwise ,it can't work anymore.
- 4).If there is no good sunlight or in winter, especially in North countries ,it may take longer time to fully charge the device and this is very normal for solar products.
- 5).The matched pole dia. 60mm

Warning:

1. Keep the device away from fire and oil in order to avoid any fire or explosion;
2. Any severe shock or smash to the light is not recommended;
3. No one except professional technicians should attempt to disassemble the light in order to avoid damaging the light.

Package include:

1. key pin: 1pc
2. Assembling bolt: 4pcs
3. Nut: 4pcs