

# Aurora A3 Pro Keychain Flashlight

## 产品说明书 (CN)

## User Manual (EN)

### 产品特征:

- CREE XP-G3 6500K 或者 5000K, 可选色温
- 330mAh 锂聚合物可充电电池
- Micro USB 充电带充电指示灯, 约 90 分钟即可充满
- 正面电子按键支持单手操作
- 橘皮光杯, 光斑更均匀
- 整体符合人体工程学设计, 提供最佳的握持手感
- 双向口袋抱夹和尾部伞绳孔设计提供多种携带方式
- 尾部支持倒立
- IP66 生活防水

### 产品参数:

材料: 7075 航空铝合金  
长度: 60.5mm 直径: 15.6mm 重量: 20 克  
包装配件: 1\*说明书, 1\*不锈钢钥匙环, 1\*不锈钢抱夹  
1\*USB 充电线, 1\*手绳, 1\*保修卡

### 操作方式:

#### 1. 照明模式

- 一键极亮: 按住开关不放, 松开即灭
- 开机: 快速双击 (默认进入记忆模式)
- 换挡: 单击循环 月光-低-中-高
- 一键极亮: 开机状态下双击, 此状态下单击进入记忆档位
- 关机: 任意档位下长按 0.3 秒;  
或者任意档位下工作超过 3 分钟, 单击关机  
记忆模式: 工作三分钟后记忆该档位, 下次开机进入记忆档位

#### 2. 爆闪

- 开机:
  - 1) 关机状态下快速三击
  - 2) 在照明模式下任意档位快速三击
- 关机: 单击

工作状态下 (非一键极亮) 快速双击或者快速三击可切换到对应档位。

注: 高亮档和中亮档工作时, 因为产生大量的热, 手电亮度会在 100 秒内降到 100 流明

### 充电:

建议收到本产品后首次使用前先将手电充满电!

- 打开位于侧面的充电口, 通过 Micro USB 线接入电源
  - 充电指示灯: 蓝色呼吸灯为充电, 蓝色常亮即充满
  - 充电时间: 90 分钟
  - 截止电压: 2.4V
- 注: 当电量低时, 充电指示灯会变红提示需充电, 单击可关闭提示。

### 警告!!

- 当手电筒点亮时, 请勿直视发光体 (LED)
- 请勿将本产品照射人眼或动物眼睛
- 年龄低于 12 岁的小孩未在监护人陪同下禁止使用本产品
- 为了产品可靠性, 筒身与筒头密封, 无法拆卸

### 质保服务:

- 保修期: 自购买日起 2 年
- 任何明显人为原因造成的功能故障或外观不良不在保修范围内

### Features:

- CREE XP-G3 6500K or 5000K LED
- Powered by built-in 330mAh Li-po rechargeable battery
- Micro USB rechargeable with charging indicator, fully charged in about 90 minutes
- E-switch supports one-handed operation
- Orange peel reflector
- Ergonomic design provides better grip and hold
- Reversible pocket clip included, and paracord hole at tail
- Tail stand capability
- IP66 weather resistance

### Parameters

Material: 7075 aerospace aluminum alloy  
Length: 60.5mm / 2.38" Diameter: 15.6mm / 0.61"  
Weight: 0.71oz  
Accessory: 1\*User Manual, 1\*SS Key ring, 1\*SS Pocket clip, 1\*USB Cable, 1\*Lanyard, 1\*Warranty Card

### Operation/User Interface

1. Illumination
  - Momentary ON: Press and Hold, release to turn off
  - Turn ON: Rapid double click (default from Memory mode)
  - Switch mode: click to cycle thru Moonlight-Low-Med-High
  - Turn Off:
    - 1) At any mode, long press the button 0.3s;
    - 2) Click to turn off when the light works at any mode over 3mins.**Memory: When the light worked at a mode over 3mins, it will be turned on from the memorized mode next time.**
2. Strobe (Emergency mode)
  - Turn ON
    - a) From off, triple click
    - b) From any mode of Illumination, triple click
  - Turn Off: Click**When the light is working (except for Momentary on), rapid double-click or rapid triple-click can switch to the related mode.**

Note: When the light is working at High mode or Medium mode, it will step down to 100 lumens in 100 seconds due to the massive heat generated.

### Charging:

Highly recommend charging the light before the first use.

- Open the USB port cover and connect to a power source thru Micro USB cable
- Charging indicator: Breathing blue is charging, Solid blue is fully charged.
- Charging time: 90 minutes
- Cutoff voltage: 2.4V







Note: If the battery is low, the indicator will come on Red to remind recharging, click the button to turn the indicator off.

### Warning!!

- DO NOT look directly into the emitter when it's ON
- DO NOT point the light at human eyes or animal eyes
- Child under 12 years old is NOT permitted to use the light unsupervised.
- The flashlight was glue sealed for the reliability, and disassembly is not under warranty.

### Warranty:

- 2 years international manufacturer warranty
- Any human-made malfunction or defective is out of warranty.

6500K/5000K	月光/Moonlight	低亮/Low	中亮/Medium	高亮/High	爆闪/Strobe
	2	20	360	700	/
	2	15	260	450	/
	30 Hours	8 Hours	1.5+95 mins	1.5+75 mins	/
	32 Hours	10 Hours	1.5+120 mins	1.5+90mins	/
	1080cd (6500K)				
	850cd (5000K)				
	90m (6500K)				
	75m (5000K)				
	1.5m				
	IP66 (weather resistance)				