# PS-12120 12 Volt 12.0 AH

**Rechargeable Sealed Lead Acid Battery** 



We've Got The Power.™









## Terminals: (mm)

- F2 Quick disconnect tabs, 0.250" x 0.032" - Mate with AMP. INC FASTON "250" series
- NB Tin plated brass posts with nut & bolt fasteners



# **Physical Dimensions: in (mm)**





F2: L: 5.94 (151) W: 3.86 (98) H: 3.66 (93) HT: 3.86 (98)

NB: L: 5.94 (151) W: 3.86 (98) H: 3.66 (93) HT: 4.09 (104)

Tolerances are +/- 0.04 in. (+/- 1mm) and +/- 0.08 in. (+/- 2mm) for height dimensions. All data subject to change without notice.

#### **Features**

- Absorbent Glass Mat (AGM) technology for superior performance
- Valve regulated, spill proof construction allows safe operation in any position
- Power/volume ratio yielding unrivaled energy density
- Rugged impact resistant ABS case and cover (UL94-HB)
- Approved for transport by air. D.O.T., I.A.T.A., F.A.A. and C.A.B. certified
- U.L. recognized under file number MH 20845


## Performance Specifications

Nominal Voltage
Nominal Capacity
20-hr. (600mA to 10.50 volts)
10-hr. (1.1A to 10.50 volts)
5-hr. (2.1A to 10.20 volts)
1-hr. (7.25A to 9.00 volts)
15-min. (21.5A to 9.00 volts)
Approximate Weight 7.92 lbs. (3.59 kg)
Energy Density (20-hr. rate) 1.69 W-h/in3 (103.41 W-h/l)
Specific Energy (20-hr. rate) 18.18 W-h/lb (40.08 W-h/kg)
Internal Resistance (approx.)
Max Discharge Current (7 Min.)
Max Short-Duration Discharge Current (10 Sec.) 120.0 amperes
Shelf Life (% of nominal capacity at 68°F (20°C)
1 Month
3 Months
6 Months
Operating Temperature Range
Charge4°F (-20°C) to 122°F (50°C)
Discharge40°F (-40°C) to 140°F (60°C)
Case


**Power-Sonic Chargers**.......PSC-122000A, 122000A-C



#### Shelf Life & Storage



## Discharge Time vs. Discharge Current



## Charging

Cycle Applications: Limit initial current to 3.6A. Charge until battery voltage (under charge) reaches 14.4 to 14.7 volts at 68°F (20°C). Hold at 14.4 to 14.7 volts until current drops to under 120mA. Battery is fully charged under these conditions, and charger should be disconnected or switched to "float" voltage.


"Float" or "Stand-By" Service: Hold battery across constant voltage source of 13.5 to 13.8 volts continuously. When held at this voltage, the battery will seek its own current level and maintain itself in a fully charged condition.

Note: Due to the self-discharge characteristics of this type of battery, it is imperative that they be charged within 6 months of storage, otherwise permanent loss of capacity might occur as a result of sulfation.


#### Chargers

Power-Sonic offers a wide range of chargers suitable for batteries up to 100AH. Please refer to the Charger Selection Guide in our specification sheets for "C-Series Switch Mode Chargers" and "Transformer Type A and F Series". Please contact our Technical department for advice if you have difficulty in locating suitable models.


## Discharge Characteristics



## Life Characteristics in Stand-By Use



#### Life Characteristics in Cyclic Use



# **Further Information**

Please refer to our website www.power-sonic.com for a complete range of useful downloads, such as product catalogs, material safety data sheets (MSDS), ISO certification, etc..

#### **Contact Information**

DOMESTIC SALES
Tel: +1-619-661-2020
Fax: +1-619-661-3650
national-sales@power-sonic.com

CUSTOMER SERVICE Tel: +1-619-661-2030 Fax: +1-619-661-3648

customer-service@power-sonic.com

TECHNICAL SUPPORT Tel: +1-619-661-2020 Fax: +1-619-661-3648 support@power-sonic.com INTERNATIONAL SALES
Tel: +1-650-364-5001
Fax: +1-650-366-3662
international-sales@power-sonic.com

www.power-sonic.com

CORPORATE OFFICE • 7550 Panasonic Way • San Diego, CA 92154 • USA • Tel: +1-619-661-2020 • Fax: +1-619-661-3650