

The ProTac Rail Mount HL-X Pro is a lightweight, low-profile long gun light that produces 50,000 candela of power. Its Jack-Cap™ tail switch offers operational switch redundancy – push-button operation or remote pressure switch operation.

Runs on either two CR123A lithium batteries or one SL-B26® USB battery pack.



TEN-TAP® programming: Choice of three operating modes: 1) high/strobe; 2) high only; 3) low/high
<ul style="list-style-type: none"> – High for maximum illumination: 1,000 lumens; 50,000 candela; 447m beam; runs 1.25 hours (CR123A); runs 1.75 hours (SL-B26®) – Low for extended run time: 60 lumens; 3,100 candela; 111m beam; runs 21 hours (CR123A); runs 24 hours (SL-B26®) – Strobe for signaling or disorienting: runs 2.5 hours (CR123A); runs 3.5 hours (SL-B26®)
One-handed snap-on & tighten interface keeps hands away from muzzle when attaching/detaching light to forend
Integrated rail clamp attaches to MIL-STD-1913 rails and M-LOK compatible rail systems

Durable, anodized aluminum construction with impact-resistant tempered glass lens
IP67-rated; waterproof to 1 meter for 30 minutes (w/o remote pressure switch installed) IP54-rated; water-resistant (with remote pressure switch installed)
5.43" (13.8 cm); 6.6 oz (187.1 g) with CR123A batteries; 7.2 oz (204.1 g) with Streamlight SL-B26® rechargeable battery
Limited Lifetime Warranty Visit streamlight.com for full warranty information
#88126 - ProTac Rail Mount HL-X Pro - Box #88127 - ProTac Rail Mount HL-X USB - Box #88128 - ProTac Rail Mount HL-X Pro - Light Only - Box #88129 - ProTac Rail Mount HL-X Pro USB - Light Only - Box

All rights reserved. M-LOK® is a registered trademark of Magpul Industries Corp.