



SPECS / FEATURES LP-EDC 5.0

Model #: 14269 Color: Grav. Black **Product Size:** 3.7 oz/ 105a 5 5" x 1 26" x 87" (140mm x 32mm x 22mm)

Max Light Output: 500 Lumens Beam Distance: approx, 305 ft Max Runtime: approx. 4 hrs (on lowest lumen mode)

Charging: USB-C Quick Charge Charge Time: approx. 2 hours Battery Type: Rechargeable 1x851750 3 7V 800mAh

LED Type: Spot = 2x CREE (white) led Weather/Drop Proof: IPX4, IK07

Durable aluminum housing

- Brushed metallic finish
- Non-slip rubber side grips
- Rear magnetic pocket clip

LP-EDC + 8.0

Model #: 14270 Color: Grav. Black **Product Size:** 3.7 oz/ 105q 5 5" x 1 26" x 87" (140mm x 32mm x



Beam Distance: approx. 338 ft Max Runtime: approx. 12 hrs (on lowest lumen mode)

Charging: USB-C Quick Charge Charge Time: approx. 2.5 hours Battery Type: Rechargeable 1x881775 3 7V 1500mAh

LED Type: Flood = COB(white & red) + Spot = 2x CREE (white) led Weather/Drop Proof: IPX4, IK07

- Hands-free magnetic base
- Protective USB-C port cover flap
- · Low battery indicator light
- Charging indicator light

OPERATION

POWER/ MODE BUTTON

- 1) Press power button to turn on.
- 2) Press power button to change modes:
- 3) After 5 seconds of no mode changes, press power button to turn off.

LP-EDC 5.0



SPOT LIGHT HIGH - 500 l m MED - 250 Lm IOW - 100 I m DIM

LP-EDC + 8.0



SPOT LIGHT HIGH - 800 I m MED - 500 Lm IOW - 200 I m DIM



HIGH - 300 Lm LOW - 100 Lm RFD - 10 l m Press & hold for

TURBO - 500 Lm

ADJUSTABLE BRIGHTNESS

LP-EDC 5.0 - PRESS & HOLD to increase/ decrease brightness. Light blinks to indicate min/max brightness level.

LP-EDC + 8.0 - PRESS & HOLD the SPOT LIGHT button to increase/ decrease brightness. Light blinks to indicate min/max brightness evel.

TURBO MODE

IP-FDC + 80 - PRESS & HOLD the FLOOD LIGHT button to boost to 500 Lumen Turbo Mode for 30 seconds.



QUESTIONS? Before returning to your retailer, call our customer service department at 704-508-1031, 8 a.m. - 5 p.m. ET. Monday - Friday or email us at info@STKRconcepts.com







- 1) Plug the USB-C cable into the USB-C port.
- 2) Plug the other end of the cable into a USB wall charger*, car charger*, or any other USB charging device* (e.g. computer). A charging indicator light inside the charging port will glow solid red while charging, and then solid green when fully charged.

*Not included. *Charger output of up to 3A is recommended. Charger output should NOT exceed 3.6A to prevent battery damage.

** To maintain optimum performance of the lithium-ion batteries and maximize charging levels, Please recharge a stored unit every four months. Battery excl. from warranty.

PACKAGE CONTENTS:

- 1) LP-EDC Light
- 1) USB-C Charge Cord

A SAFETY WARNING

This product contains high intensity LED devices.

To prevent permanent eye damage, do not stare into the light beam at close range.









1 Year warranty



